CMM720 Firmware Update Method

Apr. 20. 2020

1. Download the F/W for CMM720 from Jensen Web site/Support. https://www.jensenmobile.com/software-updates.html



Software Downloads & Instructions

Below are links to software/firmware update pages per product. If the product is not listed here then no update is available at this time.

Multimedia

- CAR10 Firmware
- CAR70V Firmware
- CAR1000 Firmware
- CMM710 Firmware
- VX2529 Firmware

MCU Firmware Update

2. Make the download folder of updated F/W file on the background of your PC.



3. Unzip the downloaded file and you can see the below folder.



4. Open the folder from unzipped folder.

파일 홈 공유 보	17							
★ ☐ ☐ 즐겨찾기에 복사 붙여넣기 고정	☆ 잘라내기 ™ 경로 복사 । 바로 가기 붙여넣기	이동 복사 위치 * 위치 *	삭제 이름 · 바꾸기	┃ 집 새 1 빠 폴더	항목 ▼ 른 연결 ▼	✓	 眞 열기 ▼ ☑ 편집 ▲ 히스토리 	
클립보드	<u> </u>	구	성	새로 만들	들기		열기	선택
2 📕 =								
← → × ↑ 🎽 > CMM	1720_6901_V00708A_Sil	ver MIC 17						~ ບ ⊂MN
	이름		만든 날짜	~	유형		크기	
📌 바로 가기	1 8268br	ncu bfu	2020-07-17	7 0저 10-27		01	76	SOKR
· 무서	020011	HCU.DIU	2020-07-17	IL 10.57	DFU H	2	10	JAND
	*							
▶ 사진	*							
도 산진 ③ SDHC (E:)	я я я							
■ 만시 ■ 사진 ③ SDHC (E:) - 내 PC	* * *							
 ▲ 사진 ③ SDHC (E:) ● 내 PC ⑤ 3D 개체 	* * *							
 ▲ 사진 ③ SDHC (E:) ● 내 PC ⑤ 3D 개체 ▲ 다운로드 	* * *							_
 ▲ 사진 ③ SDHC (E:) ● 내 PC ⑤ 3D 개체 ● 다운로드 ⑥ 동영상 	* * *							_
 ▲ 사진 ③ SDHC (E:) > 내 PC ③ 3D 개체 ▶ 다운로드 ■ 동영상 逐 문서 	*							
 ▲ 사진 ③ SDHC (E:) > 내 PC ▲ 3D 개체 ▲ 다운로드 ▲ 동영상 № 문서 ▲ 바탕 화면 	*							
 사진 SDHC (E:) JD 개체 다운로드 동영상 문서 바탕 화면 사진 	*							
 ▲ 사진 ③ SDHC (E:) ③ JD 개체 ▲ 다운로드 ■ 동영상 짙 문서 ▲ 바탕 화면 ▲ 사진 ③ 음악 	*							
 ▲ 사진 ③ SDHC (E:) ● 내 PC ③ 3D 개체 ● 다운로드 ⓐ 동영상 ○ 문서 ● 바탕 화면 ↓ 사진 ● 음악 <	*							

5. Find the updated firmware file, 8268hmcu file, and copy it into your USB Thumb Drive.

	.)	관리									
파일 홈	공유 보기	드라이브 도-	ı								
★ 즐겨찾기에 복사 고정	[] ↓ 전 전 전 전 전 전 전 전 전 전 전 전 전 전 전 전 전 전	잘라내기 경로 복사 바로 가기 붙여넣	기 이동 위치	복사 위치 ·	× 삭제	미름 바꾸기	시 생 폴더	집 새 항목 ▼ 1 빠른 연결 ▼	✓ 속성	다 열기 ▼ 2 편집 중 히스토리	■ 모두 응 선택 ● 선택
	클립보드			구성	성		새	로 만들기		열기	1
- 📕											
$\leftarrow \ \rightarrow \ \checkmark \ \uparrow$	① > 내 PC >	USB 드라이브 (F:)								~ Ū
		^ 이름				만든	날짜	~	유형	크기	
✓ ★ 바로 가기 № 문서	×	8268	3hmcu.bfu			2020)-07-17 🖣	오전 10:41	BFU 파일	7	69KB
▶ 사진	*	e									
SDHC (E:)	×	e la									
✔ 🍃 내 PC											
> 📙 3D 개체											
> 📜 다운로드											
> 📜 동영상											
> 🖻 문서											
> 늘 바탕 화면											
> = 사신											
> 기음악											
> 도걸 니스=	1 (C:)										
› 및 USB 드라이	브 (F:)										

6. Insert the USB thumb drive that contains 8268hmcu file into the USB Slot of CMM720 unit in the radio mode as below.

Image: Second state Image: Second state<	
BAND LOCAL/DX STERED AS/PS	
$\begin{bmatrix} 1 \\ 87.50 \\ 90.10 \\ 98.10 \\ 106.10 \\ 107.90 \\ 107.90 \\ 107.90 \\ 107.90 \\ 107.90 \\ 107.90 \\ 107.90 \\ 107.90 \\ 100 \\ 1$	87.50

7. When inserting the USB Thumb Drive with MCU Firmware into the USB port of the unit, the screen below is displayed after completing the Auto Update. Press the **Green** $\sqrt{$ **Icon**.



8. If you press the Green $\sqrt{}$ Icon, the Firmware Update proceeds and ACC Off / On after a short time after completion.

SK	Upgrading.Do not power off!	
	JENSEN	
2.14		



CPU Firmware Update

9. Make the download folder of updated F/W file on the background of your PC.







11. Open the folder from unzipped folder.

🖹 CMM720_202006	523A						
파일 홈 공	응유 보기						
★ ▲ ▲ ▲ ▲ ▲ ▲ ▲ ★ ▲ ▲ ★ ▲ ★ ▲ ★ ▲ ★	[]	기 특사 ト기 붙여넣기	이동 복 위치 * 위	유사 치 · · ·	미 류 이름 바꾸기	┃ 집 새 항목 ▼ 1 빠른 연결 ▼ 새 폴더	▲ 월 열기 ▼ ▲ 편집 ▼ ● 히스토리
	클립보드			구성		새로 만들기	열기
☑ 📜 ਵ							
← → ∽ ↑ 🖡	> CMM720_2020	0623A					
		이름		만든 날짜	~	유형	크기
★ 바로 가기		🖶 dydrom	i i	2020-07-17	7 오전 10:	46 ALZip BIN File	8.468KB
Market 전 1	*						0,100110
■ 사신	×						
J SDHC (E:)	ж						
나 PC							
📙 3D 개체							
다운로드							
📕 동영상							
🛅 문서							
= 바탕 화면							
▶ 사진							
▶ 음악							
🍤 로컬 디스크	(C:)						
🥪 Data (D:)							

12. Find the updated firmware file, dvdrom file, and copy it into your USB Thumb Drive.

Ĵ USB 드라이브 (F:)	관리				
파일 홈 공유 보기	드라이브 도구				
★ 1 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	라내기 로 복사 ·로 가기 붙여넣기 이동 복 위치 ~ 위:	····································	¶ 새 항목 ▼ 1 빠른 연결 ▼ 로 만들기	 ▲ 열기 * · 편집 ▲ 히스토리 열기 	문 모 응 선 문 선
🛃 📜 =					
← → ∽ ↑ 🗊 > 내 PC > U	JSB 드라이브 (F:)				~ 1
	^ 이름	만든 날짜	유형	크기	
★ 바로 가기 [™] 문서 ★ [™] 사진 ★ [®] SDHC (E:) ★	🕎 dvdrom	2020-07-17 오전 10:51	ALZip BIN	8,468KB	
 ▶ 내 PC ▶ 3D 개체 ▶ 다운로드 > 동영상 > 문서 > 바탕 화면 ▶ 사진 > 음악 > Data (D:) > SDHC (E:) > USB 드라이브 (F:) 					

13. Insert the USB thumb drive that contains dvdrom file into the USB Slot of CMM720 unit in the radio mode as below.

HC MC	🕀 Ra	adio			12	:46 рм	
t S	«	_{FM1}]()7.	.90	LOC P1 MHz	•	
SR L		BAND		OD STERED	AS/P	s	
	¹ 87.50	90.10	³ 98.10	^₄ 106.10	₅ 107.90	⁶ 87.50	
2.1A	[<u>@</u> (4	JENS	EN			

14. You can see the below screenshot and press Green $\sqrt{$ Icon. In a few seconds, the update is started.



15. Once the update is started successfully, you can see Green color bar to show the status.

	Upgrading.Do not power off!	
XX ITT		
Z.1A	JENSEN	

16. When firmware update is completed, and power of CMM720 is off, you can remove your USB thumb drive.



Checked Update Firmware Version

17. Press the Setting Icon on the Main Menu Screen or Radio Mode Screen.

	adio			12	:46 м
	FM1] ()7.	.90	LOC P1 MHz	•
	BAND		OD STERED	AS/P	 s
° ¹ 87.5	0 ² 90.10	³ 98.10	₄ 106.10	₅ 107.90	⁶ 87.50
	<u>e</u>) = JENS	- EN		

18. You can touch the arrow at the bottom right of the screen of General Setup, and find the updated firmware version Icon that has been complete as below. And Pressed the Version Icon to check the updated Firmware Version.

Sett	ing 💼 🔹 12:46 ам 🍮
	Beep Camera Version Restore Default
L.1A	I I I I I I I I I I I I I I I I I I I